



## Tecpel Model DCM-2606 1000A Clamp Meter

**Sale Price      => \$115 plus GST**



- 1000A Amp AC/DC True R.M.S.
- 3 3/4 digit display with bargraph
- AC/DC current up to 1000A
- AC voltage up to 750V
- DC voltage up to 1000V
- Display hold function
- True-RMS reading
- Diode test
- Carrying case
- Audible continuity test
- Overrange indication
- Frequency up to 400KHz
- Capacitance measurement
- Resistance up to 40M ohm
- Relative mode to read offset values (Zero  $\Delta$ Key)
- Peak hold for transient measurements
- Max/Min recording mode Model : DCM 2606
- Confirm to the IEC-1010-1,UL1244/UL3111, CE standard
- Hand guard protection

- Specifications of DCM-2606 Clamp Meter
  - DC Voltage Ranges:
    - 400mV,4V,40V,400V,1000V, +/--(0.5%+1dgt)
  - AC Voltage Ranges:
    - True RMS 400mV,4V,40V,400V,750V,+/--(1.5%+4dgts)
  - AC Current Ranges:
    - True RMS 400A,1000A,+/--(1.5%+5dgts)
  - DC Current Ranges:
    - 400A,1000A,+/--(1.5%+5dgts)
  - Clamp Meter Resistance Ranges:
    - 400 ,4k,40k,400k,4M ,40M ,+/--(1%+2dgts)
  - Frequency Ranges:
    - 100,1k,10k,100k,400kHz, +/--(0.5%+3dgts)
  - Continuity Test:
    - Audible indication 400 Ohm,Threshold
  - General
    - Power Requirement:
      - One 9V battery
    - Dimensions:
      - 10.8"x3.6"x1.7" (275x90x43mm)
    - Weight:17 oz(482g)
    - Accessories:
      - Test leads, soft carrying case, battery, and owners manual